

Ser. No. 10/605,534
Art Unit: 2816

3

Printed 3/28/2005

In the claims:

Please cancel claim 1 and amend claim 7 as follows:

5 1. (canceled)

10 2. (withdrawn) The voltage sensor circuit of claim 1 wherein the first current source is a substrate-sensing transistor having a substrate node driven by the source-input voltage and a gate driven by a constant bias voltage, the substrate-sensing transistor conducting the first current between the stable node and the compare-input node,
wherein the first current through the substrate-sensing transistor varies with variations in the source-input voltage,
whereby a substrate-sensing current source generates the first current.

15

3. (withdrawn) The voltage sensor circuit of claim 2 wherein the substrate-sensing transistor is a p-channel transistor and the substrate node is an N-well.

20 4. (withdrawn) The voltage sensor circuit of claim 3 wherein the constant bias voltage is a ground.

25 5. (withdrawn) The voltage sensor circuit of claim 4 wherein the second current source is a second p-channel transistor having a substrate node connected to the stable node and a gate driven by the constant bias voltage, the second p-channel transistor conducting the second current between the stable node and the reference node.

30 6. (withdrawn) The voltage sensor circuit of claim 5 wherein a cross-over voltage of the source-input voltage that causes the output voltage to change states varies less than +/- 8% over a temperature range from -40 to +85 degrees C.

7. (currently amended) A voltage sensor circuit comprising:

Ser. No. 10/605,534
Art Unit: 2816

4

Printed 3/28/2005

- a source-input node having a source-input voltage that is varied by a voltage source, the
voltage sensor circuit sensing the source-input voltage of the source-input node;
a first current source, responsive to the source-input voltage, for generating a first current
that varies with variations in the source-input voltage;
5 a first resistor, coupled to the first current source and receiving the first current, for
generating a compare-input voltage on a compare-input node in response to the
first current, the compare-input voltage varying with variations in the first current;
a second current source for generating a second current that is insensitive to variations in
the source-input voltage;
10 a second resistor, coupled to the second current source and receiving the second current,
for generating a reference voltage on a reference node in response to the second
current, the reference voltage varying with variations in the second current;
a stable node, coupled to the first current source and coupled to the second current
source, the stable node having a stable voltage that is relatively insensitive to
15 changes in a supply voltage;
a comparator coupled to the compare-input node and the reference node, for comparing
the compare-input voltage to the reference voltage and generating an output
voltage at an output node that indicates when the compare-input voltage is above
the reference voltage;
20 ~~The voltage sensor circuit of claim 1~~ wherein the first current source comprises:
a first mirror transistor having a channel that conducts the first current between the stable
node and the compare-input node in response to a first gate node;
a first setting transistor, with a gate connected to the first gate node, having a channel that
conducts a first setting current between the stable node and the first gate node;
25 a first sensing transistor having a channel that conducts a portion of the first setting
current from the first gate node, the first sensing transistor having a gate
connected to the source-input voltage;
wherein the second current source comprises:
a second mirror transistor having a channel that conducts the second current between the
30 stable node and the reference node in response to a second gate node;

Ser. No. 10/605,534
Art Unit: 2816

5

Printed 3/28/2005

a second setting transistor, with a gate connected to the second gate node, having a channel that conducts a second setting current between the stable node and the second gate node; and

5 a second sensing transistor having a channel that conducts a portion of the second setting current from the second gate node, the second sensing transistor having a gate connected to a fixed voltage.

8. (original) The voltage sensor circuit of claim 7 wherein the fixed voltage applied to the gate of the second sensing transistor is the stable voltage.

10

9. (original) The voltage sensor circuit of claim 8 wherein the first and second mirror transistors and the first and second setting transistors are p-channel transistors; wherein the first and second sensing transistors are n-channel transistors.

15 10. (original) The voltage sensor circuit of claim 9 wherein a cross-over voltage of the source-input voltage that causes the output voltage to change states varies less than +/- 4% over a temperature range from -40 to +85 degrees C.

20 11. (previously amended) The voltage sensor circuit of claim 7 further comprising: a voltage generator for generating the stable voltage on the stable node that is independent of the supply voltage to the comparator.

12. (original) The voltage sensor circuit of claim 11 wherein the voltage generator is a band-gap voltage generator.

25

13. (original) The voltage sensor circuit of claim 12 wherein the comparator is powered by the supply voltage.

30 14. (withdrawn) A substrate-sensing voltage sensor comprising: a voltage generator for generating a stable voltage on a stable node, the stable voltage being relatively insensitive to variations in a supply voltage;

Ser. No. 10/605,534
Art Unit: 2816

6

Printed 3/28/2005

a comparator that generates an output by comparing voltages of a compare-input node
and a reference node;

a first transistor having a channel connected between the stable node and the compare-
input node, with a gate connected to a bias voltage and a substrate connected to a
source-input voltage that is varied by a voltage source;

a first resistor connected between the compare-input node and a ground;

a second transistor having a channel connected between the stable node and the reference
node, with a gate connected to the bias voltage; and

a second resistor connected between the reference node and the ground,

whereby the source-input voltage from the voltage source is sensed by substrate-sensing
of the first transistor.

15. (withdrawn) The substrate-sensing voltage sensor of claim 14 wherein the first
transistor is a p-channel transistor with a source connected to the stable node, a
drain connected to the compare-input node, and the source-input voltage
connected to a n-type substrate or an N-well under the first transistor;
wherein the second transistor is a p-channel transistor with a source connected to the
stable node, a drain connected to the reference node, and the stable voltage
connected to a n-type substrate or an N-well under the second transistor.

20

16. (withdrawn) The substrate-sensing voltage sensor of claim 15 wherein the bias
voltage is the ground,
whereby the first and second transistors have grounded gates.

25 17. (previously amended) A temperature-insensitive voltage sensor comprising:
an input voltage from a varying voltage source;
compare means, having a first input and a second input, for comparing voltages on the
first and second inputs to generate an output;
first resistor means, receiving a first current, for generating a compare voltage on the first
input of the compare means;

30

Ser. No. 10/605,534
Art Unit: 2816

7

Printed 3/28/2005

first mirror transistor means, having a gate connected to a first gate node, for generating the first current from a stable node to the first input of the compare means and to the first resistor means;

5 first current-source transistor means, having a gate and a drain connected to the first gate node and a source connected to the stable node, for generating a first gate voltage on the first gate node;

first sensing transistor means, having a gate driven by the input voltage, for varying a first sink current from the first gate node in response to the input voltage;

10 second resistor means, receiving a second current, for generating a reference voltage on the second input of the compare means;

second mirror transistor means, having a gate connected to a second gate node, for generating the second current from the stable node to the second input of the compare means and to the second resistor means;

15 second current-source transistor means, having a gate and a drain connected to the second gate node and a source connected to the stable node, for generating a second gate voltage on the second gate node; and

second sensing transistor means, having a gate driven by a constant voltage, for generating a second sink current from the second gate node.

20 18. (original) The temperature-insensitive voltage sensor of claim 17 further comprising: stable-voltage generator means for generating a stable voltage on the stable node, the stable voltage being insensitive to a supply voltage to the compare means.

25 19. (original) The temperature-insensitive voltage sensor of claim 18 wherein the first and second sensing transistor means are n-channel transistors having grounded sources;

wherein the first and second mirror transistor means are p-channel transistors having sources connected to the stable node;

30 wherein the first and second current-source transistor means are p-channel transistors having sources connected to the stable node and each having a drain shorted to a gate.

Ser. No. 10/605,534
Art Unit: 2816

8

Printed 3/28/2005

20. (previously amended) The temperature-insensitive voltage sensor of claim 19 wherein the constant voltage to the gate of the second sensing transistor means is the stable voltage.

5